

## COMPREHENSIVE SERVICES

We offer competitive repair and calibration services, as well as easily accessible documentation and free downloadable resources.

## SELL YOUR SURPLUS

We buy new, used, decommissioned, and surplus parts from every NI series. We work out the best solution to suit your individual needs.

 Sell For Cash    Get Credit    Receive a Trade-In Deal

## OBSOLETE NI HARDWARE IN STOCK & READY TO SHIP

We stock **New**, **New Surplus**, **Refurbished**, and **Reconditioned** NI Hardware.



A P E X W A V E S

*Bridging the gap between the manufacturer and your legacy test system.*



1-800-915-6216



[www.apexwaves.com](http://www.apexwaves.com)



[sales@apexwaves.com](mailto:sales@apexwaves.com)

All trademarks, brands, and brand names are the property of their respective owners.

***Request a Quote***

 **CLICK HERE**

***USB-7845***

SPECIFICATIONS

# NI USB-7845R OEM

R Series for USB Multifunction RIO with Kintex-7 70T FPGA

|                |         |     |     |      |
|----------------|---------|-----|-----|------|
| Français       | Deutsch | 日本語 | 한국어 | 简体中文 |
| ni.com/manuals |         |     |     |      |

This document contains the specifications for the National Instruments USB-7845R OEM device. Specifications are typical at 25 °C unless otherwise noted.



**Caution** Using the NI USB-7845R OEM device in a manner not described in this document may impair the protection the NI USB-7845R OEM device provides.

## Analog Input

|                            |  |
|----------------------------|--|
| Number of channels.....    | 8  |
| Input modes.....           | DIFF, NRSE, RSE (software-selectable; selection applies to all channels) |
| Type of ADC.....           | Successive approximation register (SAR)                                  |
| Resolution.....            | 16 bits  |
| Conversion time.....       | 2 $\mu$ s  |
| Maximum sampling rate..... | 500 kS/s (per channel)   |
| Input impedance            |  |
| Powered on.....            | 1.25 G $\Omega$    2 pF  |
| Powered off/overload.....  | 4.0 k $\Omega$ min   |
| Input signal range.....    | $\pm 1$ V, $\pm 2$ V, $\pm 5$ V, $\pm 10$ V (software-selectable)        |
| Input bias current.....    | $\pm 5$ nA   |
| Input offset current.....  | $\pm 5$ nA   |
| Input coupling.....        | DC   |
| Overvoltage protection     |  |
| Powered on.....            | $\pm 42$ V max   |
| Powered off.....           | $\pm 35$ V max   |

**Table 1.** AI Operating Voltage Ranges Over Temperature

| Range | Measurement Voltage, AI+ to AI- |         |         | Maximum Working Voltage<br>(Signal + Common Mode) |
|-------|---------------------------------|---------|---------|---|
|       | Min (V) <sup>1</sup>            | Typ (V) | Max (V) |   |
| ±10 V | ±10.37                          | ±10.5   | ±10.63  | ±12 V of ground                                   |
| ±5 V  | ±5.18                           | ± 5.25  | ±5.32   | ±10 V of ground                                   |
| ±2 V  | ±2.07                           | ±2.1    | ±2.13   | ±8.5 V of ground                                  |
| ±1 V  | ±1.03                           | ±1.05   | ±1.06   | ±8 V of ground                                    |

## AI Absolute Accuracy

Absolute accuracy at full scale numbers is valid immediately following internal calibration and assumes the device is operating within 10 °C of the last external calibration. Accuracies listed are valid for up to one year from the device external calibration.

Absolute accuracy at full scale on the analog input channels is determined using the following assumptions:

- TempChangeFromLastExternalCal = 10 °C
- TempChangeFromLastInternalCal = 1 °C
- number\_of\_readings = 10,000
- CoverageFactor = 3  $\sigma$

**Table 2.** AI Absolute Accuracy (Calibrated)

| Specifications                              | Range |       |       |       |
|---|-------|-------|-------|-------|
|   | ±10 V | ±5 V  | ±2 V  | ±1 V  |
| <b>Residual Gain Error (ppm of Reading)</b> | 104.4 | 105.9 | 110.6 | 118.4 |
| <b>Gain Tempco (ppm/°C)</b>                 | 20    | 20    | 20    | 20    |
| <b>Reference Tempco (ppm/°C)</b>            | 4     | 4     | 4     | 4     |
| <b>Residual Offset Error (ppm of Range)</b> | 16.4  | 16.4  | 16.4  | 16.4  |
| <b>Offset Tempco (ppm of Range/°C)</b>      | 4.18  | 4.17  | 4.41  | 4.63  |
| <b>INL Error (ppm of range)</b>             | 42.52 | 46.52 | 46.52 | 50.52 |

<sup>1</sup> The minimum measurement voltage range is the largest voltage the NI USB-7845R OEM device is guaranteed to accurately measure.

**Table 2.** AI Absolute Accuracy (Calibrated) (Continued)

| Specifications   | Range |       |      |      |
|--|-------|-------|------|------|
|  | ±10 V | ±5 V  | ±2 V | ±1 V |
| <b>Random Noise, <math>\sigma</math> (<math>\mu\text{V}_{\text{rms}}</math>)</b> | 263   | 156   | 90   | 74   |
| <b>Absolute Accuracy at Full Scale (<math>\mu\text{V}</math>)</b>                | 2,283 | 1,170 | 479  | 252  |

**Table 3.** AI Absolute Accuracy (Uncalibrated)

| Specifications   | Range  |        |       |       |
|--|--------|--------|-------|-------|
|  | ±10 V  | ±5 V   | ±2 V  | ±1 V  |
| <b>Residual Gain Error (ppm of Reading)</b>                                      | 2,921  | 3,021  | 3,021 | 3,021 |
| <b>Gain Tempco (ppm/°C)</b>  | 20     | 20     | 20    | 20    |
| <b>Reference Tempco (ppm/°C)</b>   | 4      | 4      | 4     | 4     |
| <b>Residual Offset Error (ppm of Range)</b>                                      | 661    | 671    | 700   | 631   |
| <b>Offset Tempco (ppm of Range/°C)</b>   | 4.18   | 4.17   | 4.41  | 4.63  |
| <b>INL Error (ppm of range)</b>  | 42.52  | 46.52  | 46.52 | 50.52 |
| <b>Random Noise, <math>\sigma</math> (<math>\mu\text{V}_{\text{rms}}</math>)</b> | 263    | 156    | 90    | 74    |
| <b>Absolute Accuracy at Full Scale (<math>\mu\text{V}</math>)</b>                | 36,895 | 19,018 | 7,667 | 3,769 |

## Calculating Absolute Accuracy

$$\text{AbsoluteAccuracy} = \text{Reading} \cdot (\text{GainError}) + \text{Range} * (\text{OffsetError}) + \text{NoiseUncertainty}$$

$$\begin{aligned} \text{GainError} = & \text{ResidualGainError} + \text{GainTempco} * (\text{TempChangeFromLastInternalCal}) \\ & + \text{ReferenceTempco} * (\text{TempChangeFromLastExternalCal}) \end{aligned}$$

$$\text{OffsetError} = \text{ResidualOffsetError} + \text{OffsetTempco} * (\text{TempChangeFromLastInternalCal}) + \text{INL\_Error}$$

$$\text{NoiseUncertainty} = \frac{\text{RandomNoise} * \text{CoverageFactor}}{\sqrt{\text{number\_of\_readings}}}$$

Refer to the following equation for an example of calculating absolute accuracy.

Absolute accuracy at full scale on the analog input channels is determined using the following assumptions:

- TempChangeFromLastExternalCal = 10 °C
- TempChangeFromLastInternalCal = 1 °C
- number\_of\_readings = 10,000
- CoverageFactor = 3  $\sigma$

$$GainError = 104.4 \text{ ppm} + 20 \text{ ppm} * 1 + 4 \text{ ppm} * 10$$

$$GainError = 164.4 \text{ ppm}$$

$$OffsetError = 16.4 \text{ ppm} + 4.18 \text{ ppm} * 1 + 42.52 \text{ ppm}$$

$$OffsetError = 63.1 \text{ ppm}$$

$$NoiseUncertainty = \frac{263 \text{ } \mu V * 3}{\sqrt{10,000}}$$

$$NoiseUncertainty = 7.89 \text{ } \mu V$$

$$AbsoluteAccuracy = 10 \text{ V} * (GainError) + 10 \text{ V} * (OffsetError) + NoiseUncertainty$$

$$AbsoluteAccuracy = 2,283 \text{ } \mu V$$

## DC Transfer Characteristics

|                        |                                |
|------------------------|--------------------------------|
| INL.....               | Refer to the AI Accuracy Table |
| DNL.....               | ±0.4 LSB typ, ±0.9 LSB max     |
| No missing codes.....  | 16 bits guaranteed             |
| CMRR, DC to 60 Hz..... | -100 dB                        |

## Dynamic Characteristics

|                   |         |
|-------------------|---------|
| Bandwidth         |         |
| Small signal..... | 1 MHz   |
| Large signal..... | 500 kHz |

# Settling Time

| Range (V) | Step Size (V) | Accuracy |         |          |
|-----------|---------------|----------|---------|----------|
|           |               | ±16 LSB  | ±4 LSB  | ±2 LSB   |
| ±10       | ±20.0         | 1.50 µs  | 3.50 µs | 7.00 µs  |
|           | ±2.0          | 0.50 µs  | 0.50 µs | 1.00 µs  |
|           | ±0.2          | 0.50 µs  | 0.50 µs | 0.50 µs  |
| ±5        | ±10           | 1.50 µs  | 3.50 µs | 7.50 µs  |
|           | ±1            | 0.50 µs  | 0.50 µs | 1.00 µs  |
|           | ±0.1          | 0.50 µs  | 0.50 µs | 0.50 µs  |
| ±2        | ±4            | 1.00 µs  | 3.50 µs | 8.00 µs  |
|           | ±0.4          | 0.50 µs  | 0.50 µs | 1.00 µs  |
|           | ±0.04         | 0.50 µs  | 0.50 µs | 0.50 µs  |
| ±1        | ±2            | 1.00 µs  | 3.50 µs | 12.00 µs |
|           | ±0.2          | 0.50 µs  | 0.50 µs | 1.00 µs  |
|           | ±0.02         | 0.50 µs  | 0.50 µs | 0.50 µs  |

Crosstalk.....-80 dB, DC to 100 kHz

# Analog Output

Output type.....Single-ended, voltage output

Number of channels.....8

Resolution.....16 bits

Update time.....1.0 µs

Maximum update rate.....1 MS/s

Type of DAC.....Enhanced R-2R

Range.....±10 V

Output coupling.....DC

Output impedance.....0.5 Ω

Minimum current drive.....±2.5 mA

Protection.....Short circuit to ground

Overvoltage protection

    Powered on.....±15 V max

    Powered off.....±10 V max

Power-on state.....User-configurable

Power-on glitch.....-1 V for 1 μs

**Table 4.** AO Operating Voltage Ranges for Over Temperature

| Range | Measurement Voltage, AO+ to AO GND |         |         |
|-------|------------------------------------|---------|---------|
|       | Min (V) <sup>2</sup>               | Typ (V) | Max (V) |
| ±10 V | ±10.1                              | ±10.16  | ±10.22  |

## AO Absolute Accuracy

Absolute accuracy at full scale numbers is valid immediately following internal calibration and assumes the device is operating within 10 °C of the last external calibration. Accuracies listed are valid for up to one year from the device external calibration.

Absolute accuracy at full scale on the analog output channels is determined using the following assumptions:

- TempChangeFromLastExternalCal = 10 °C
- TempChangeFromLastInternalCal = 1 °C

**Table 5.** AO Absolute Accuracy (Calibrated)

| Specifications                       | ±10 V Range |
|--------------------------------------|-------------|
| Residual Gain Error (ppm of Reading) | 87.3        |
| Gain Tempco (ppm/°C)                 | 12.6        |
| Reference Tempco (ppm/°C)            | 4           |
| Residual Offset Error (ppm of Range) | 41.1        |
| Offset Tempco (ppm of Range/°C)      | 7.8         |

<sup>2</sup> The minimum measurement voltage range is the largest voltage the NI USB-7845R OEM device is guaranteed to accurately measure.

**Table 5. AO Absolute Accuracy (Calibrated) (Continued)**

| Specifications                       | ±10 V Range |
|--------------------------------------|-------------|
| INL Error (ppm of range)             | 61          |
| Absolute Accuracy at Full Scale (µV) | 2,498       |

**Table 6. AO Absolute Accuracy (Uncalibrated)**

| Specifications                       | ±10 V Range |
|--------------------------------------|-------------|
| Residual Gain Error (ppm of Reading) | 2,968.6     |
| Gain Tempco (ppm/°C)                 | 12.6        |
| Reference Tempco (ppm/°C)            | 4           |
| Residual Offset Error (ppm of Range) | 1,004.1     |
| Offset Tempco (ppm of Range/°C)      | 7.8         |
| INL Error (ppm of range)             | 61          |
| Absolute Accuracy at Full Scale (µV) | 40,941      |

## Calculating Absolute Accuracy

$$\text{AbsoluteAccuracy} = \text{OutputValue} * (\text{GainError}) + \text{Range} * (\text{OffsetError})$$

$$\begin{aligned} \text{GainError} = & \text{ResidualGainError} + \text{GainTempco} * (\text{TempChangeFromLastInternalCal}) \\ & + \text{ReferenceTempco} * (\text{TempChangeFromLastExternalCal}) \end{aligned}$$

$$\text{OffsetError} = \text{ResidualOffsetError} + \text{AOOffsetTempco} * (\text{TempChangeFromLastInternalCal}) + \text{INL\_Error}$$

Refer to the following equation for an example of calculating absolute accuracy.

Absolute accuracy at full scale on the analog output channels is determined using the following assumptions:

- TempChangeFromLastExternalCal = 10 °C
- TempChangeFromLastInternalCal = 1 °C

$$\text{GainError} = 87.3 \text{ ppm} + 12.6 \text{ ppm} * 1 + 4 \text{ ppm} * 10$$

$$\text{GainError} = 139.9 \text{ ppm}$$



$$\text{OffsetError} = 41.1 \text{ ppm} + 7.8 \text{ ppm} * 1 + 61 \text{ ppm}$$

$$\text{OffsetError} = 109.9 \text{ ppm}$$

$$\text{AbsoluteAccuracy} = 10 \text{ V} * (\text{GainError}) + 10 \text{ V} * (\text{OffsetError})$$

$$\text{AbsoluteAccuracy} = 2,498 \text{ }\mu\text{V}$$

## DC Transfer Characteristics

INL.....Refer to the AO Accuracy Table

DNL.....±0.5 LSB typ, ±1 LSB max

Monotonicity.....16 bits, guaranteed

## Dynamic Characteristics

**Table 7. Settling Time**

| Step Size | Accuracy |        |        |
|-----------|----------|--------|--------|
|           | ±16 LSB  | ±4 LSB | ±2 LSB |
| ±20.0 V   | 5.1 μs   | 5.8 μs | 7.5 μs |
| ±2.0      | 3.0 μs   | 3.7 μs | 4.3 μs |
| ±0.2      | 1.7 μs   | 2.9 μs | 3.4 μs |

Slew rate.....-10 V/μs

Noise.....250 μV<sub>rms</sub>, DC to 1 MHz

Glitch energy at midscale transition.....±10 mV for 3 μs

## 5V Output

Output voltage.....4.75 V to 5.1 V

Output current.....0.5 A max

Overvoltage protection.....±30 V

Overcurrent protection.....650 mA

# Digital I/O

**Table 8.** Channel Frequency

| Connector   | Number of Channels | Maximum Frequency |
|-------------|--------------------|-------------------|
| Connector 1 | 16                 | 10 MHz            |
| Connector 2 | 16                 | 10 MHz            |
| Connector 3 | 16                 | 10 MHz            |

Compatibility.....LVTTTL  
Logic family.....User-selectable  
Default software setting.....3.3 V

**Table 9.** Digital Input Logic Levels

| Logic Family | Input Low Voltage, $V_{IL}$ (Max) | Input High Voltage, $V_{IH}$ (Min) |
|--------------|-----------------------------------|------------------------------------|
| 1.2 V        | 0.42 V                            | 0.84 V                             |
| 1.5 V        | 0.51 V                            | 1.01 V                             |
| 1.8 V        | 0.61 V                            | 1.21 V                             |
| 2.5 V        | 0.70 V                            | 1.60 V                             |
| 3.3 V        | 0.80 V                            | 2.00 V                             |

Maximum input.....3.6 V

**Table 10.** Digital Output Logic Levels

| Logic Family | Current     | Output Low Voltage, $V_{OL}$ (Max) | Output High Voltage, $V_{OH}$ (Min) |
|--------------|-------------|------------------------------------|-------------------------------------|
| 1.2 V        | 100 $\mu$ A | 0.20 V                             | 1.00 V                              |
| 1.5 V        | 100 $\mu$ A | 0.20 V                             | 1.25 V                              |
| 1.8 V        | 100 $\mu$ A | 0.20 V                             | 1.54 V                              |
| 2.5 V        | 100 $\mu$ A | 0.20 V                             | 2.22 V                              |

**Table 10.** Digital Output Logic Levels (Continued)

| Logic Family | Current     | Output Low Voltage, $V_{OL}$ (Max) | Output High Voltage, $V_{OH}$ (Min) |
|--------------|-------------|------------------------------------|-------------------------------------|
| 3.3 V        | 100 $\mu$ A | 0.20 V                             | 3.00 V                              |
|              | 4 mA        | 0.40 V                             | 2.40 V                              |

Output current

Source.....4.0 mA

Sink.....4.0 mA

Input leakage current..... $\pm 15$   $\mu$ A max

Input impedance.....50 k $\Omega$  typ, pull-down

Power-on state.....Programmable, by line

Protection..... $\pm 20$  V, single line

Digital I/O voltage switching time.....2 ms max



**Note** Refer to *NI RIO Software Help* for more information about switching times.

## Reconfigurable FPGA

FPGA type.....Kintex-7 70T

Number of flip-flops.....82,000

Number of LUTs.....41,000

Embedded block RAM.....4,860 kbits

Number of DSP48 slices.....240

Timebase.....40, 80, 120, 160, or 200 MHz

Timebase accuracy, onboard clock..... $\pm 100$  ppm

## Calibration

Recommended warm-up time.....15 minutes

Calibration interval.....1 year

Onboard calibration reference

|                         |                 |
|-------------------------|-----------------|
| DC level <sup>3</sup>   | 5.000 V (±2 mV) |
| Temperature coefficient | ±4 ppm/°C max   |
| Long-term stability     | ±25 ppm/1,000 h |



**Note** Refer to Calibration Certifications at [ni.com/calibration](https://ni.com/calibration) to generate a calibration certificate for the NI USB-7845R OEM device

# Bus Interface

---

|                        |   |
|------------------------|---|
| USB compatibility      | USB 2.0 Hi-Speed or Full-Speed <sup>4</sup> |
| Data transfers         | DMA, interrupts, programmed I/O             |
| Number of DMA channels | 3   |

# Power Requirement

---

|                        |             |
|------------------------|-------------|
| Input voltage          | 9 V to 30 V |
| Max power              | 20 W        |
| Overvoltage protection | 40 V        |



**Note** You must use a UL Listed ITE power supply marked LPS with the NI USB-7845R OEM device.

# Physical

---



**Note** If you need to clean the device, wipe it with a dry, clean towel.

|                  |  |
|------------------|--|
| Dimensions (PCB) | 17.5 cm × 16.3 cm (6.9 in. × 6.4 in.)                            |
| Weight           | 183 g (6.45 oz)  |
| I/O connectors   | Analog- 1 × 50 pin box header,<br>Digital- 3 × 34 pin box header |

---

<sup>3</sup> Actual value stored in Flash memory  
<sup>4</sup> Operating on a full-speed bus will result in lower performance and you might not be able to achieve maximum sampling/update rates.

# Maximum Working Voltage

---

Maximum working voltage refers to the signal voltage plus the common-mode voltage.

Channel-to-earth.....±12 V, Measurement Category I

Channel-to-channel.....±24 V, Measurement Category I

Measurement Category I is for measurements performed on circuits not directly connected to the electrical distribution system referred to as MAINS voltage. MAINS is a hazardous live electrical supply system that powers equipment. This category is for measurements of voltages from specially protected secondary circuits. Such voltage measurements include signal levels, special equipment, limited-energy parts of equipment, circuits powered by regulated low-voltage sources, and electronics.



**Caution** Do not use the NI USB-7845R OEM device for connection to signals in Measurement Categories II, III, or IV.



**Note** Measurement Categories CAT I and CAT O (Other) are equivalent. These test and measurement circuits are not intended for direct connection to the MAINS building installations of Measurement Categories CAT II, CAT III, or CAT IV.

# Environmental

---

Operating temperature.....-40 °C to 70 °C  
(IEC 60068-2-1, IEC 60068-2-2)

Storage temperature.....-40 °C to 85 °C  
(IEC 60068-2-1, IEC 60068-2-2)

Operating humidity.....10% to 90% RH, noncondensing  
(IEC 60068-2-56)

Storage humidity (IEC 60068-2-56).....5% to 95% RH, noncondensing

Pollution Degree.....2

Maximum altitude.....2,000 m

Indoor use only.

# Online Product Certification

---

To obtain product certifications and the DoC for this product, visit [ni.com/certification](https://ni.com/certification), search by model number or product line, and click the appropriate link in the Certification column.

# Environmental Management

---

NI is committed to designing and manufacturing products in an environmentally responsible manner. NI recognizes that eliminating certain hazardous substances from our products is beneficial to the environment and to NI customers.

For additional environmental information, refer to the *Minimize Our Environmental Impact* web page at [ni.com/environment](https://ni.com/environment). This page contains the environmental regulations and directives with which NI complies, as well as other environmental information not included in this document.

## Waste Electrical and Electronic Equipment (WEEE)

---



**EU Customers** At the end of the product life cycle, all products must be sent to a WEEE recycling center. For more information about WEEE recycling centers, National Instruments WEEE initiatives, and compliance with WEEE Directive 2002/96/EC on Waste Electrical and Electronic Equipment, visit [ni.com/environment/weee](https://ni.com/environment/weee).

## 电子信息产品污染控制管理办法（中国 RoHS）

---



**中国客户** National Instruments 符合中国电子信息产品中限制使用某些有害物质指令 (RoHS)。关于 National Instruments 中国 RoHS 合规性信息，请登录 [ni.com/environment/rohs\\_china](https://ni.com/environment/rohs_china)。(For information about China RoHS compliance, go to [ni.com/environment/rohs\\_china](https://ni.com/environment/rohs_china).)

## Worldwide Support and Services

---

The National Instruments website is your complete resource for technical support. At [ni.com/support](https://ni.com/support), you have access to everything from troubleshooting and application development self-help resources to email and phone assistance from NI Application Engineers.

Visit [ni.com/services](https://ni.com/services) for NI Factory Installation Services, repairs, extended warranty, and other services.

Visit [ni.com/register](https://ni.com/register) to register your National Instruments product. Product registration facilitates technical support and ensures that you receive important information updates from NI.

National Instruments corporate headquarters is located at 11500 North Mopac Expressway, Austin, Texas, 78759-3504. National Instruments also has offices located around the world. For telephone support in the United States, create your service request at [ni.com/support](https://ni.com/support) or

dial 1 866 ASK MYNI (275 6964). For telephone support outside the United States, visit the *Worldwide Offices* section of [ni.com/niglobal](http://ni.com/niglobal) to access the branch office websites, which provide up-to-date contact information, support phone numbers, email addresses, and current events.

Refer to the *NI Trademarks and Logo Guidelines* at [ni.com/trademarks](http://ni.com/trademarks) for information on National Instruments trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering National Instruments products/technology, refer to the appropriate location: **Help»Patents** in your software, the `patents.txt` file on your media, or the *National Instruments Patent Notice* at [ni.com/patents](http://ni.com/patents). You can find information about end-user license agreements (EULAs) and third-party legal notices in the readme file for your NI product. Refer to the *Export Compliance Information* at [ni.com/legal/export-compliance](http://ni.com/legal/export-compliance) for the National Instruments global trade compliance policy and how to obtain relevant HTS codes, ECCNs, and other import/export data.

© 2014 National Instruments. All rights reserved.