

COMPREHENSIVE SERVICES

INSTRUMENTS

We offer competitive repair and calibration services, as well as easily accessible documentation and free downloadable resources.



SELL YOUR SURPLUS

We buy new, used, decommissioned, and surplus parts from every NI series. We work out the best solution to suit your individual needs.



Sell For Cash



Get Credit



Receive a Trade-In Deal

OBSOLETE NI HARDWARE IN STOCK & READY TO SHIP

We stock **New, New Surplus, Refurbished, and Reconditioned** NI Hardware.



Request a Quote

✉ CLICK HERE

PCI-6030E



Bridging the gap between the manufacturer and your legacy test system.

📞 1-800-915-6216

🌐 www.apexwaves.com

✉ sales@apexwaves.com

All trademarks, brands, and brand names are the property of their respective owners.

NI 6030E/6031E/6032E/6033E Family Specifications

This document lists the I/O terminal summary and specifications for the devices that make up the NI 6030E family of devices. This family includes the following devices:

- NI PXI-6030E
- NI PCI-MIO-16XE-10 (NI 6030E)
- NI PCI-6031E
- NI PXI-6031E
- NI PCI-6032E
- NI PCI-6033E

I/O Terminal Summary



Note With NI-DAQmx, National Instruments revised its terminal names so they are easier to understand and more consistent among NI hardware and software products. The revised terminal names used in this document are usually similar to the names they replace. For a complete list of Traditional NI-DAQ (Legacy) terminal names and their NI-DAQmx equivalents, refer to *Terminal Name Equivalents* of the *E Series Help*.

Table 1. I/O Terminals

Terminal Name	Terminal Type and Direction	Impedance Input/Output	Protection (V) On/Off	Source (mA at V)	Sink (mA at V)	Rise Time (ns)	Bias
AI <0..15>, AI <16..63> [†]	AI	100 GΩ in parallel with 100 pF	25/15	—	—	—	±1 nA
AI SENSE, AI SENSE 2 [‡]	AI	100 GΩ in parallel with 100 pF	25/15	—	—	—	±1 nA
AI GND	—	—	—	—	—	—	—
AO 0 [‡]	AO	0.1 Ω	Short-circuit to ground	5 at 10	5 at -10	5 V/μs	—
AO 1 [‡]	AO	0.1 Ω	Short-circuit to ground	5 at 10	5 at -10	5 V/μs	—
AO GND	—	—	—	—	—	—	—
D GND	—	—	—	—	—	—	—

Table 1. I/O Terminals (Continued)

Terminal Name	Terminal Type and Direction	Impedance Input/Output	Protection (V) On/Off	Source (mA at V)	Sink (mA at V)	Rise Time (ns)	Bias
+5 V	—	0.1 Ω	Short-circuit to ground	1 A	—	—	—
P0.<0..7>	DIO	—	V _{CC} + 0.5	13 at (V _{CC} – 0.4)	24 at 0.4	1.1	50 kΩ pu
AI HOLD COMP	DO	—	—	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
EXT STROBE*	DO	—	—	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
PFI 0/ (AI START TRIG)	AI/DIO	10 kΩ	V _{CC} + 0.5/±35	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	9 kΩ pu, 10 kΩ pd
PFI 1/ (AI REF TRIG)	DIO	—	V _{CC} + 0.5	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
PFI 2/ (AI CONV CLK)*	DIO	—	V _{CC} + 0.5	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
PFI 3/ CTR 1 SOURCE	DIO	—	V _{CC} + 0.5	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
PFI 4/CTR 1 GATE	DIO	—	V _{CC} + 0.5	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
CTR 1 OUT	DO	—	—	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
PFI 5/ (AO SAMP CLK)*	DIO	—	V _{CC} + 0.5	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
PFI 6/ (AO START TRIG)	DIO	—	V _{CC} + 0.5	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
PFI 7/ (AI SAMP CLK)	DIO	—	V _{CC} + 0.5	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
PFI 8/ CTR 0 SOURCE	DIO	—	V _{CC} + 0.5	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
PFI 9/CTR 0 GATE	DIO	—	V _{CC} + 0.5	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu
CTR 0 OUT	DO	—	—	3.5 at (V _{CC} – 0.4)	5 at 0.4	1.5	50 kΩ pu

Table 1. I/O Terminals (Continued)

Terminal Name	Terminal Type and Direction	Impedance Input/Output	Protection (V) On/Off	Source (mA at V)	Sink (mA at V)	Rise Time (ns)	Bias
FREQ OUT	DO	—	—	3.5 at ($V_{CC} - 0.4$)	5 at 0.4	1.5	50 kΩ pu

* Indicates active low.
 † NI 6031E/6033E only.
 ‡ NI 6030E/6031E only.

AI = Analog Input DIO = Digital Input/Output pd = pull-down
 AO = Analog Output DO = Digital Output pu = pull-up
 AI/DIO = Analog Input/Digital Input/Output

Note: The tolerance on the 50 kΩ pull-up resistors is large. Actual value might range between 17 kΩ and 100 kΩ.

Specifications

The following specifications are typical at 25 °C unless otherwise noted.

Analog Input

Input Characteristics

Number of channels

- NI 6030E, NI 6032E..... 16 single-ended or 8 differential (software-selectable per channel)
- NI 6031E, NI 6033E..... 64 single-ended or 32 differential (software-selectable per channel)

Type of A/D converter (ADC)..... Successive approximation

Resolution 16 bits, 1 in 65,536

Max sampling rate (single-channel)¹ 100 kS/s guaranteed

Input signal ranges

Range (Software-Selectable)	Input Range	
	Bipolar	Unipolar
20 V	±10 V	—
10 V	±5 V	0 to 10 V
5 V	—	0 to 5 V
4 V	±2 V	—
2 V	±1 V	0 to 2 V
1 V	±500 mV	0 to 1 V
500 mV	—	0 to 500 mV
400 mV	±200 mV	—
200 mV	±100 mV	0 to 200 mV
100 mV	—	0 to 100 mV

¹ Refer to the *Settling time* table in the [Dynamic Characteristics](#) section for multichannel rates.

Input coupling.....DC

Max working voltage.....Each input should remain
within ± 11 V of ground.

Overvoltage protection

Powered on ± 25 V

Powered off ± 15 V

Inputs protected

NI 6030E, NI 6032EAI <0..15>, AI SENSE

NI 6031E, NI 6033EAI <0..63>, AI SENSE,
AI SENSE 2

FIFO buffer size

NI PCI-6031E OEM1,024 samples (S)

All other devices512 S

DMA

Channels.....3

Data sources/destinations.....Analog input, analog
output, counter/timer 0,
or counter/timer 1

Data transfers.....Direct memory access
(DMA), interrupts,
programmed I/O

DMA modesScatter-gather
(single-transfer,
demand-transfer)

Configuration memory size512 words
(1 word = 8 bits)

Accuracy Information

Nominal Range (V)		Absolute Accuracy							Relative Accuracy Resolution (μ V)	
Positive Full Scale	Negative Full Scale	% of Reading		Offset (μ V)	Noise + Quantization (μ V)		Temp Drift (%/ $^{\circ}$ C)	Absolute Accuracy at Full Scale (mV)		
		24 Hours	1 Year		Single Pt.	Averaged		Single Pt.	Averaged	
+10.0	-10.0	0.0044	0.0061	479.2	634.1	54.9	0.0001	1.147	723.3	72.3
+5.0	-5.0	0.0344	0.0361	243.6	317.1	27.5	0.0006	2.077	361.6	36.2
+2.0	-2.0	0.0344	0.0361	102.2	126.8	11.0	0.0006	0.836	144.7	14.5
+1.0	-1.0	0.0344	0.0361	55.1	63.4	5.5	0.0006	0.422	72.3	7.2
+0.5	-0.5	0.0344	0.0361	31.6	36.8	3.2	0.0006	0.215	42.2	4.2
+0.2	-0.2	0.0394	0.0411	17.4	22.5	2.0	0.0006	0.102	26.5	2.7
+0.1	-0.1	0.0044	0.0461	12.7	19.6	1.8	0.0006	0.061	24.1	2.4
10.0	0.0	0.0044	0.0061	326.6	417.8	36.6	0.0001	0.976	482.2	48.2
5.0	0.0	0.0344	0.0361	167.3	208.9	18.3	0.0006	1.992	241.1	24.1
2.0	0.0	0.0344	0.0361	71.7	83.6	7.3	0.0006	0.802	96.4	9.6
1.0	0.0	0.0344	0.0361	39.9	41.8	3.7	0.0006	0.405	48.2	4.8
0.5	0.0	0.0344	0.0361	23.9	28.1	2.5	0.0006	0.207	33.1	3.3
0.2	0.0	0.0394	0.0411	14.4	19.6	1.8	0.0006	0.098	24.1	2.4
0.1	0.0	0.0444	0.0461	11.2	18.1	1.7	0.0006	0.059	22.9	2.3

Note: Accuracies are valid for measurements following an internal E Series calibration. Averaged numbers assume dithering and averaging of 100 single-channel readings. Measurement accuracies are listed for operational temperatures within ± 1 $^{\circ}$ C of internal calibration temperature and ± 10 $^{\circ}$ C of external or factory-calibration temperature. NI recommends a one-year calibration interval. The Absolute Accuracy at Full Scale calculations were performed for a maximum range input voltage (for example, 10 V for the ± 10 V range) after one year, assuming 100 points of averaged data. Go to ni.com/info and enter info code rdspec for example calculations.

Transfer Characteristics

Relative accuracy	± 0.75 LSB typ, ± 1 LSB max
Differential nonlinearity (DNL)	± 0.5 LSB typ, ± 1 LSB max
No missing codes.....	16 bits, guaranteed
Offset error	
Pregain error after calibration	± 3 μ V max
Pregain error before calibration	± 2.2 mV max
Postgain error after calibration	± 76 μ V max
Postgain error before calibration	± 102 mV max
Gain error (relative to calibration reference)	
After calibration (gain = 1)	± 30.5 ppm of reading max
Before calibration	$\pm 2,150$ ppm of reading max
With gain error adjusted to 0 at gain = 1	
Gain $\neq 1$	± 200 ppm of reading max

Amplifier Characteristics

Input impedance	
Normal, powered on	100 G Ω in parallel with 100 pF
Powered off.....	820 Ω min
Overload.....	820 Ω min
Input bias current.....	± 1 nA
Input offset current	± 2 nA

Common-mode rejection ratio (CMRR), DC to 60 Hz

Range	CMRR	
	Bipolar (dB)	Unipolar (dB)
20 V	92	—
10 V	97	92
5 V	—	97
4 V	101	—
2 V	104	101
1 V	105	104
100 mV to 500 mV	105	105

Dynamic Characteristics

Bandwidth (-3 dB)	
All gains.....	255 kHz

Settling time for full-scale step (DC to all gains and ranges)

Device	Accuracy*		
	$\pm 0.00076\%$ (± 0.5 LSB)	$\pm 0.0015\%$ (± 1 LSB)	$\pm 0.0061\%$ (± 4 LSB)
NI 6030E	40 μ s max	20 μ s max	10 μ s max
NI 6032E	50 μ s max	25 μ s max	10 μ s max
NI 6031E	50 μ s max	25 μ s max	10 μ s max
NI 6033E			

* Accuracy values are valid for source impedances <1 k Ω . Refer to *Multichannel Scanning Considerations* of the *E Series Help* for more information.

System noise (LSB_{rms}, including quantization)

Range	Bipolar	Unipolar
2 to 20 V	0.6	0.8
1 V	0.7	0.8
400 to 500 mV	1.1	1.1
200 mV	2.0	2.0
100 mV	—	3.8

Crosstalk (DC to 100 kHz)

Adjacent channels	-75 dB
All other channels.....	-90 dB

Stability

Offset temperature coefficient

Pregain	$\pm 5 \mu\text{V}/^\circ\text{C}$
Postgain	$\pm 120 \mu\text{V}/^\circ\text{C}$

Gain temperature coefficient..... $\pm 8 \text{ ppm}/^\circ\text{C}$

Analog Output (NI 6030E/6031E Only)

Output Characteristics

Number of channels 2 voltage

Resolution 16 bits, 1 in 65,536

Max update rate 100 kS/s

Type of digital-to-analog converter (DAC) Double-buffered

FIFO buffer size 2,048 samples (S)

Data transfers DMA, interrupts, programmed I/O

DMA modes Scatter-gather
(single-transfer,
demand-transfer)

Accuracy Information

Nominal Range (V)		Absolute Accuracy				Absolute Accuracy at Full Scale (mV)	
Positive Full Scale	Negative Full Scale	% of Reading			Offset (μV)	Temp Drift ($%/^\circ\text{C}$)	
		24 Hours	90 Days	1 Year			
10	-10	0.0045	0.0053	0.0062	812.8	0.0001	1.430
10	0	0.0045	0.0053	0.0062	583.9	0.0001	1.201

Note: Accuracies are valid for measurements following an internal E Series calibration. Averaged numbers assume dithering and averaging of 100 single-channel readings. Measurement accuracies are listed for operational temperatures within $\pm 1^\circ\text{C}$ of internal calibration temperature and $\pm 10^\circ\text{C}$ of external or factory-calibration temperature. NI recommends a one-year calibration interval. The Absolute Accuracy at Full Scale calculations were performed for a maximum range input voltage (for example, 10 V for the ± 10 V range) after one year, assuming 100 points of averaged data. Go to ni.com/info and enter info code `rdspec` for example calculations.

Transfer Characteristics

Relative accuracy,
or integral nonlinearity (INL) ± 0.5 LSB typ,
 ± 1 LSB max

DNL ± 1 LSB max

Monotonicity 16 bits, guaranteed

Offset error

After calibration	$305 \mu\text{V}$ max
Before calibration	20 mV max

Gain error (relative to internal reference)

After calibration	$\pm 30.5 \text{ ppm}$ max
Before calibration	$\pm 2,000 \text{ ppm}$ max

Voltage Output

Range.....	± 10 V, 0 to 10 V (software-selectable)
Output coupling.....	DC
Output impedance.....	0.1 Ω max
Current drive.....	± 5 mA
Protection.....	Short-circuit to ground
Power-on state	0 V (± 20 mV)

Dynamic Characteristics

Settling time for full-scale step	10 μ s to ± 1 LSB accuracy
Slew rate.....	5 V/ μ s
Noise.....	60 μ V _{rms} , DC to 1 MHz

Stability

Offset temperature coefficient.....	± 50 μ V/ $^{\circ}$ C
Gain temperature coefficient.....	± 7.5 ppm/ $^{\circ}$ C

Digital I/O

Number of channels.....	8 input/output
Compatibility.....	5 V TTL/CMOS

Digital logic levels on P0.<0..7>

Level	Min	Max
Input low voltage	0 V	0.8 V
Input high voltage	2.0 V	5.0 V
Input low current ($V_{in} = 0$ V)	—	-320 μ A
Input high current ($V_{in} = 5$ V)	—	10 μ A
Output low voltage ($I_{OL} = 24$ mA)	—	0.4 V
Output high voltage ($I_{OH} = -13$ mA)	4.35 V	—

Power-on state Input (high-impedance)

Data transfers.....Programmed I/O

Transfer rate

Maximum with NI-DAQ,
system-dependent.....50 kwords/s
Constant suitable rate.....1 to 10 kwords/s, typ

Timing I/O

Number of channels

Up/down counter/timers	2
Frequency scaler.....	1

Resolution

Up/down counter/timers	24 bits
Frequency scaler.....	4 bits

Compatibility 5 V TTL/CMOS

Digital logic levels

Level	Min	Max
Input low voltage	0.0 V	0.8 V
Input high voltage	2.0 V	5.0 V
Output low voltage ($I_{out} = 5$ mA)	—	0.4 V
Output high voltage ($I_{out} = -3.5$ mA)	4.35 V	—

Base clocks available

Up/down counter/timers	20 MHz, 100 kHz
Frequency scaler.....	10 MHz, 100 kHz

Base clock accuracy..... $\pm 0.01\%$

Max external source frequency

up/down counter/timers 20 MHz

External source selections.....PFI <0..9>, RTSI <0..6>,
analog trigger,
software-selectable

External gate selections PFI <0..9>, RTSI <0..6>,
analog trigger,
software-selectable

Min source pulse duration.....10 ns in edge-detect mode

Min gate pulse duration 10 ns in edge-detect mode

Data transfers

PCI/PXI up/down
counter/timer DMA (scatter-gather),
interrupts,
programmed I/O

DAQCard up/down
counter/timer DMA (scatter-gather),
interrupts,
programmed I/O

Frequency scaler.....Programmed I/O

Triggers

Analog Trigger

Purpose

Analog input	Start, reference, and pause trigger, sample clock
Analog output	Start and pause trigger, sample clock
Counter/timers	Source, gate
Source	
NI 6030E, NI 6032E	AI <0..15>, PFI 0/AI START TRIG
NI 6031E, NI 6033E	AI <0..63>, PFI 0/AI START TRIG
Level	
Internal	±Full scale
External	±10 V
Slope	Positive or negative (software-selectable)
Resolution	12 bits, 1 in 4,096
Hysteresis	Programmable
Bandwidth (-3 dB)	
PCI devices	255 kHz internal, 4 MHz external
PXI devices	255 kHz internal/external
External input (PFI 0/AI START TRIG)	
Impedance	10 kΩ
Coupling	DC
Protection	
When configured as a digital signal	0.5 to VCC + 0.5 V
When configured as an analog signal or disabled	±35 V
Powered off	±35 V
Accuracy	±1% of full-scale range

Digital Trigger

Purpose

Analog input	Start, reference, and pause trigger, sample clock
Analog output	Start and pause trigger, sample clock
Counter/timers	Source, gate
External sources	PFI <0..9>, RTSI <0..6>

Compatibility.....5 V TTL

Response.....Rising or falling edge

Pulse width10 ns min

RTSI (PCI Only)

Trigger lines7

PXI Trigger Bus (PXI Only)

Trigger lines6

Star trigger.....1

Calibration

Recommended warm-up time15 minutes

Calibration interval.....1 year

External calibration referenceBetween 6 and 9.999 V

Onboard calibration reference

Level5.000 V (±1.0 mV), over full operating temperature, actual value stored in EEPROM

Temperature coefficient.....±0.6 ppm/°C max

Long-term stability±6 ppm/√1,000 h

Bus Interface

Type.....Master, slave

Power

Bus Requirements

+5 VDC (±5%).....1.5 A



Note Excludes power consumed through V_{CC} available at the I/O connector.

I/O Connector

Power available at I/O connector+4.65 to +5.25 VDC at 1 A

Physical

Dimensions (not including connectors)

PCI devices17.5 cm × 10.6 cm
(6.9 in. × 4.2 in.)

PXI devices16.0 cm × 10.0 cm
(6.3 in. × 3.9 in.)

Weight

NI PCI-MIO-16XE-10/

NI PXI-6031E211 g (7.4 oz)

NI PXI-6030E232 g (8.1 oz)

NI PCI-6031E	199 g (7.0 oz)
NI PCI-6032E	185 g (6.5 oz)
NI PCI-6033E	179 g (6.2 oz)
I/O connector	
NI 6030E, NI 6032E	68-pin male SCSI-II type
NI 6031E, NI 6033E	100-pin female 0.05 D-type

Maximum Working Voltage

Maximum working voltage refers to the signal voltage plus the common-mode voltage.

Channel-to-earth	11 V, Installation Category I
Channel-to-channel	11 V, Installation Category I

Environmental

Operating temperature	0 to 50 °C
Storage temperature	-20 to 70 °C
Relative humidity	
PCI devices	10 to 90%, noncondensing
PXI devices	10 to 90%, noncondensing
Maximum altitude	2,000 meters
Pollution Degree (indoor use only)	2

Safety

This product is designed to meet the requirements of the following standards of safety for electrical equipment for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1
- CAN/CSA-C22.2 No. 61010-1



Note For UL and other safety certifications, refer to the product label, or visit ni.com/certification, search by model number or product line, and click the appropriate link in the Certification column.

Electromagnetic Compatibility

Emissions	EN 55011 Class A at 10 m FCC Part 15A above 1 GHz
Immunity	EN 61326:1997 A2:2001, Table 1
CE, C-Tick, and FCC Part 15 (Class A) Compliant	



Note For EMC compliance, you must operate this device with shielded cabling.

CE Compliance

This product meets the essential requirements of applicable European Directives, as amended for CE marking, as follows:

Low-Voltage Directive (safety) 73/23/EEC

Electromagnetic Compatibility

Directive (EMC) 89/336/EEC



Note Refer to the Declaration of Conformity (DoC) for this product for any additional regulatory compliance information. To obtain the DoC for this product, visit ni.com/certification, search by model number or product line, and click the appropriate link in the Certification column.



AI 8	34	68	AI 0
AI 1	33	67	AI GND
AI GND	32	66	AI 9
AI 10	31	65	AI 2
AI 3	30	64	AI GND
AI GND	29	63	AI 11
AI 4	28	62	AI SENSE
AI GND	27	61	AI 12
AI 13	26	60	AI 5
AI 6	25	59	AI GND
AI GND	24	58	AI 14
AI 15	23	57	AI 7
AO 0	22	56	AI GND
AO 1	21	55	AO GND
AO EXT REF	20	54	AO GND
P0.4	19	53	D GND
D GND	18	52	P0.0
P0.1	17	51	P0.5
P0.6	16	50	D GND
D GND	15	49	P0.2
+5 V	14	48	P0.7
D GND	13	47	P0.3
D GND	12	46	AI HOLD COMP
PFI 0/AI START TRIG	11	45	EXT STROBE
PFI 1/AI REF TRIG	10	44	D GND
D GND	9	43	PFI 2/AI CONV CLK
+5 V	8	42	PFI 3/CTR 1 SRC
D GND	7	41	PFI 4/CTR 1 GATE
PFI 5/AO SAMP CLK	6	40	CTR 1 OUT
PFI 6/AO START TRIG	5	39	D GND
D GND	4	38	PFI 7/AI SAMP CLK
PFI 9/CTR 0 GATE	3	37	PFI 8/CTR 0 SRC
CTR 0 OUT	2	36	D GND
FREQ OUT	1	35	D GND

Figure 1. NI PXI-6030E/PCI-MIO-16XE-10 Pinout

AI GND	1	51	AI 16
AI GND	2	52	AI 24
AI 0	3	53	AI 17
AI 8	4	54	AI 25
AI 1	5	55	AI 18
AI 9	6	56	AI 26
AI 2	7	57	AI 19
AI 10	8	58	AI 27
AI 3	9	59	AI 20
AI 11	10	60	AI 28
AI 4	11	61	AI 21
AI 12	12	62	AI 29
AI 5	13	63	AI 22
AI 13	14	64	AI 30
AI 6	15	65	AI 23
AI 14	16	66	AI 31
AI 7	17	67	AI 32
AI 15	18	68	AI 40
AI SENSE	19	69	AI 33
AO 0	20	70	AI 41
AO 1	21	71	AI 34
AO EXT REF	22	72	AI 42
AO GND	23	73	AI 35
D GND	24	74	AI 43
P0.0	25	75	AI SENSE 2
P0.4	26	76	AI GND
P0.1	27	77	AI 36
P0.5	28	78	AI 44
P0.2	29	79	AI 37
P0.6	30	80	AI 45
P0.3	31	81	AI 38
P0.7	32	82	AI 46
D GND	33	83	AI 39
+5 V	34	84	AI 47
+5 V	35	85	AI 48
AI HOLD COMP	36	86	AI 56
EXT STROBE	37	87	AI 49
PFI 0/AI START TRIG	38	88	AI 57
PFI 1/AI REF TRIG	39	89	AI 50
PFI 2/AI CONV CLK	40	90	AI 58
PFI 3/CTR 1 SRC	41	91	AI 51
PFI 4/CTR 1 GATE	42	92	AI 59
CTR 1 OUT	43	93	AI 52
PFI 5/AO SAMP CLK	44	94	AI 60
PFI 6/AO START TRIG	45	95	AI 53
PFI 7/AI SAMP CLK	46	96	AI 61
PFI 8/CTR 0 SRC	47	97	AI 54
PFI 9/CTR 0 GATE	48	98	AI 62
CTR 0 OUT	49	99	AI 55
FREQ OUT	50	100	AI 63

Figure 2. NI 6031E Pinout

AI 8	34	68	AI 0
AI 1	33	67	AI GND
AI GND	32	66	AI 9
AI 10	31	65	AI 2
AI 3	30	64	AI GND
AI GND	29	63	AI 11
AI 4	28	62	AI SENSE
AI GND	27	61	AI 12
AI 13	26	60	AI 5
AI 6	25	59	AI GND
AI GND	24	58	AI 14
AI 15	23	57	AI 7
NC	22	56	AI GND
NC	21	55	AO GND
NC	20	54	AO GND
P0.4	19	53	D GND
D GND	18	52	P0.0
P0.1	17	51	P0.5
P0.6	16	50	D GND
D GND	15	49	P0.2
+5 V	14	48	P0.7
D GND	13	47	P0.3
D GND	12	46	AI HOLD COMP
PFI 0/AI START TRIG	11	45	EXT STROBE
PFI 1/AI REF TRIG	10	44	D GND
D GND	9	43	PFI 2/AI CONV CLK
+5 V	8	42	PFI 3/CTR 1 SRC
D GND	7	41	PFI 4/CTR 1 GATE
PFI 5/AO SAMP CLK	6	40	CTR 1 OUT
PFI 6/AO START TRIG	5	39	D GND
D GND	4	38	PFI 7/AI SAMP CLK
PFI 9/CTR 0 GATE	3	37	PFI 8/CTR 0 SRC
CTR 0 OUT	2	36	D GND
FREQ OUT	1	35	D GND

NC = No Connect

Figure 3. NI 6032E Pinout

AI GND	1	51	AI 16
AI GND	2	52	AI 24
AI 0	3	53	AI 17
AI 8	4	54	AI 25
AI 1	5	55	AI 18
AI 9	6	56	AI 26
AI 2	7	57	AI 19
AI 10	8	58	AI 27
AI 3	9	59	AI 20
AI 11	10	60	AI 28
AI 4	11	61	AI 21
AI 12	12	62	AI 29
AI 5	13	63	AI 22
AI 13	14	64	AI 30
AI 6	15	65	AI 23
AI 14	16	66	AI 31
AI 7	17	67	AI 32
AI 15	18	68	AI 40
AI SENSE	19	69	AI 33
NC	20	70	AI 41
NC	21	71	AI 34
NC	22	72	AI 42
AO GND	23	73	AI 35
D GND	24	74	AI 43
P0.0	25	75	AI SENSE 2
P0.4	26	76	AI GND
P0.1	27	77	AI 36
P0.5	28	78	AI 44
P0.2	29	79	AI 37
P0.6	30	80	AI 45
P0.3	31	81	AI 38
P0.7	32	82	AI 46
D GND	33	83	AI 39
+5 V	34	84	AI 47
+5 V	35	85	AI 48
AI HOLD COMP	36	86	AI 56
EXT STROBE	37	87	AI 49
PFI 0/AI START TRIG	38	88	AI 57
PFI 1/AI REF TRIG	39	89	AI 50
PFI 2/AI CONV CLK	40	90	AI 58
PFI 3/CTR 1 SRC	41	91	AI 51
PFI 4/CTR 1 GATE	42	92	AI 59
CTR 1 OUT	43	93	AI 52
PFI 5/AO SAMP CLK	44	94	AI 60
PFI 6/AO START TRIG	45	95	AI 53
PFI 7/AI SAMP CLK	46	96	AI 61
PFI 8/CTR 0 SRC	47	97	AI 54
PFI 9/CTR 0 GATE	48	98	AI 62
CTR 0 OUT	49	99	AI 55
FREQ OUT	50	100	AI 63

NC = No Connect

Figure 4. NI 6033E Pinout

National Instruments, NI, ni.com, and LabVIEW are trademarks of National Instruments Corporation. Refer to the *Terms of Use* section on ni.com/legal for more information about National Instruments trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering National Instruments products, refer to the appropriate location: **Help»Patents** in your software, the *patents.txt* file on your CD, or ni.com/patents.