

COMPREHENSIVE SERVICES

We offer competitive repair and calibration services, as well as easily accessible documentation and free downloadable resources.

SELL YOUR SURPLUS

We buy new, used, decommissioned, and surplus parts from every NI series. We work out the best solution to suit your individual needs.

 Sell For Cash  Get Credit  Receive a Trade-In Deal

OBSOLETE NI HARDWARE IN STOCK & READY TO SHIP

We stock **New**, **New Surplus**, **Refurbished**, and **Reconditioned** NI Hardware.



Bridging the gap between the manufacturer and your legacy test system.

 1-800-915-6216

 www.apexwaves.com

 sales@apexwaves.com

All trademarks, brands, and brand names are the property of their respective owners.

Request a Quote

 **CLICK HERE**

PCI-6601

NOTE TO USERS

NI 66xx Pinout Labels for the SCB-68

Counter/Timer Modules/Devices Using the 68-Pin Shielded Connector Block

If you are using an NI 66xx (formerly referred to as TIO) counter/timer device or module with the SCB-68, you can print and attach a connector-specific pinout label to the cover of the connector block for easy connection reference. This document provides labels for the following models:

- NI 6601
- NI 6602
- NI 6608
- NI 6612
- NI 6614

Use the following label if you are connecting the SCB-68 to NI 6601, NI 6602, and NI 6608 models.

Figure 1. NI 660x




SCB-68 Quick Reference Label
NI 660x Counter/Timer (TIO) Models




DIO/CTR		DIO/CTR		DIO/CTR	
68	D GND	12	PFI 3/P0.3	1	+5 V
34	PFI 31/P0.31/CTR 2 SOURCE	46	D GND	35	R GND
67	PFI 30/P0.30/CTR 2 GATE	13	PFI 4/P0.4	2	PFI 39/CTR 0 SOURCE
33	D GND	47	PFI 5/P0.5	36	D GND
66	PFI 29/P0.29/CTR 2 AUX	14	D GND	3	PFI 38/CTR 0 GATE
32	PFI 28/P0.28/CTR 2 OUT	48	PFI 6/P0.6	37	RESERVED
65	D GND	15	PFI 7/P0.7	4	RESERVED
31	PFI 27/P0.27/CTR 3 SOURCE	49	D GND	38	RESERVED
64	PFI 26/P0.26/CTR 3 GATE	16	PFI 8/P0.8/CTR 7 OUT	5	PFI 36/CTR 0 OUT
30	D GND	50	D GND	39	D GND
63	PFI 25/P0.25/CTR 3 AUX	17	PFI 9/P0.9/CTR 7 AUX	6	PFI 33/CTR 1 AUX
29	PFI 24/P0.24/CTR 3 OUT	51	PFI 10/P0.10/CTR 7 GATE	40	PFI 37/CTR 0 AUX
62	D GND	18	D GND	7	PFI 35/CTR 1 SOURCE
28	PFI 23/P0.23/CTR 4 SOURCE	52	PFI 11/P0.11/CTR 7 SOURCE	41	D GND
61	PFI 22/P0.22/CTR 4 GATE	19	R GND	8	PFI 34/CTR 1 GATE
27	D GND	53	PFI 12/P0.12/CTR 6 OUT	42	D GND
60	PFI 21/P0.21/CTR 4 AUX	20	D GND	9	PFI 32/CTR 1 OUT
26	PFI 20/P0.20/CTR 4 OUT	54	PFI 13/P0.13/CTR 6 AUX	43	R GND
59	D GND	21	PFI 14/P0.14/CTR 6 GATE	10	PFI 0/P0.0
25	PFI 19/P0.19/CTR 5 SOURCE	55	D GND	44	PFI 1/P0.1
58	PFI 18/P0.18/CTR 5 GATE	22	PFI 15/P0.15/CTR 6 SOURCE	11	D GND
24	D GND	56	R GND	45	PFI 2/P0.2
57	PFI 17/P0.17/CTR 5 AUX				
23	PFI 16/P0.16/CTR 5 OUT				

R GND: These terminals are routed to RESERVED when using the product with a SH68-68-D1 shielded cable or routed to D GND when using the product with a R68-68 ribbon cable.



Use the following label if you are connecting the SCB-68 to NI 6612 and NI 6614 models.

Figure 2. NI 661x



SCB-68 Quick Reference Label
NI 661x Counter/Timer (TIO) Models

DIO/CTR

68	D GND
34	PFI 31/P0.31/CTR 2 SOURCE
67	PFI 30/P0.30/CTR 2 GATE
33	D GND
66	PFI 29/P0.29/CTR 2 AUX
32	PFI 28/P0.28/CTR 2 OUT
65	D GND
31	PFI 27/P0.27/CTR 3 SOURCE
64	PFI 26/P0.26/CTR 3 GATE
30	D GND
63	PFI 25/P0.25/CTR 3 AUX
29	PFI 24/P0.24/CTR 3 OUT
62	D GND
28	PFI 23/P0.23/CTR 4 SOURCE
61	PFI 22/P0.22/CTR 4 GATE
27	D GND
60	PFI 21/P0.21/CTR 4 AUX
26	PFI 20/P0.20/CTR 4 OUT
59	D GND
25	PFI 19/P0.19/CTR 5 SOURCE
58	PFI 18/P0.18/CTR 5 GATE
24	D GND
57	PFI 17/P0.17/CTR 5 AUX
23	PFI 16/P0.16/CTR 5 OUT

DIO/CTR


12	PFI 3/P0.3
46	D GND
13	PFI 4/P0.4
47	PFI 5/P0.5
14	D GND
48	PFI 6/P0.6
15	PFI 7/P0.7
49	D GND
16	PFI 8/P0.8/CTR 7 OUT
50	D GND
17	PFI 9/P0.9/CTR 7 AUX
51	PFI 10/P0.10/CTR 7 GATE
18	D GND
52	PFI 11/P0.11/CTR 7 SOURCE
19	R GND
53	PFI 12/P0.12/CTR 6 OUT
20	D GND
54	PFI 13/P0.13/CTR 6 AUX
21	PFI 14/P0.14/CTR 6 GATE
55	D GND
22	PFI 15/P0.15/CTR 6 SOURCE
56	R GND

DIO/CTR

1	+5 V
35	R GND
2	PFI 39/P1.7/CTR 0 SOURCE
36	D GND
3	PFI 38/P1.6/CTR 0 GATE
37	RESERVED
4	RESERVED
38	RESERVED
5	PFI 36/P1.4/CTR 0 OUT
39	D GND
6	PFI 33/P1.1/CTR 1 AUX
40	PFI 37/P1.6/CTR 0 AUX
7	PFI 35/P1.3/CTR 1 SOURCE
41	D GND
8	PFI 34/P1.2/CTR 1 GATE
42	D GND
9	PFI 32/P1.0/CTR 1 OUT
43	R GND
10	PFI 0/P0.0
44	PFI 1/P0.1
11	D GND
45	PFI 2/P0.2

R GND: These terminals are routed to RESERVED when using the product with a SH68-68-D1 shielded cable
or routed to D GND when using the product with a R68-68 ribbon cable.

Direct Feedthrough



Refer to the *NI Trademarks and Logo Guidelines* at ni.com/trademarks for more information on NI trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering NI products/technology, refer to the appropriate location: **Help»Patents** in your software, the `patents.txt` file on your media, or the *National Instruments Patents Notice* at ni.com/patents. You can find information about end-user license agreements (EULAs) and third-party legal notices in the `readme` file for your NI product. Refer to the *Export Compliance Information* at ni.com/legal/export-compliance for the NI global trade compliance policy and how to obtain relevant HTS codes, ECCNs, and other import/export data. NI MAKES NO EXPRESS OR IMPLIED WARRANTIES AS TO THE ACCURACY OF THE INFORMATION CONTAINED HEREIN AND SHALL NOT BE LIABLE FOR ANY ERRORS. U.S. Government Customers: The data contained in this manual was developed at private expense and is subject to the applicable limited rights and restricted data rights as set forth in FAR 52.227-14, DFAR 252.227-7014, and DFAR 252.227-7015.

© 2018 National Instruments. All rights reserved.