

## COMPREHENSIVE SERVICES

We offer competitive repair and calibration services, as well as easily accessible documentation and free downloadable resources.

## SELL YOUR SURPLUS

We buy new, used, decommissioned, and surplus parts from every NI series. We work out the best solution to suit your individual needs.

 Sell For Cash    Get Credit    Receive a Trade-In Deal

## OBSOLETE NI HARDWARE IN STOCK & READY TO SHIP

We stock **New**, **New Surplus**, **Refurbished**, and **Reconditioned** NI Hardware.



*Bridging the gap between the manufacturer and your legacy test system.*

 1-800-915-6216

 [www.apexwaves.com](http://www.apexwaves.com)

 [sales@apexwaves.com](mailto:sales@apexwaves.com)

All trademarks, brands, and brand names are the property of their respective owners.

**Request a Quote**

 **CLICK HERE**

**PCI-MXI-2**

## INSTALLATION GUIDE

# NI-VXI™/NI-VISA™ for the PCI-MXI-2 for Linux

This installation guide describes system requirements, gives installation instructions, and includes support information for NI-VXI/NI-VISA for the PCI-MXI-2 interface for the Linux operating system.

## System Requirements

---

NI-VXI for Linux requires the following system components:

- Linux kernel 2.4.x or 2.6.x for the Intel x86 architecture
- Support for building kernel modules (included with all major Linux distributions)

Recommended Linux distributions are:

- RedHat Enterprise Linux
- SuSE Linux
- Mandrake Linux

## Installation Instructions

---

Before you begin, you may need to install Linux on your computer. Refer to your Linux distribution documentation for instructions. Install the PCI-MXI-2 as described in the *Getting Started with Your VXI/VME-PCI8026 and the NI-VXI/NI-VISA Software for Linux* manual. After your computer is booted into Linux, you are ready to install the NI-VXI/NI-VISA software.

To install NI-VXI/NI-VISA for the PCI-MXI-2 for Linux, perform the following steps:

1. Insert the *NI-VXI/NI-VISA for Linux* CD.
2. Log in to your system as `root`.

3. Mount the CD-ROM.
4. To change the current directory to the mounted CD-ROM, type the following command:  

```
cd /media/cdrom
```



**Note** This command may vary depending on your Linux distribution.

5. To run the installation script, type the following command:  

```
./INSTALL
```

The `INSTALL` script places NI-VXI and NI-VISA in their default locations in `/usr/local`. The script uses `rpm` to install the packages. The script also optionally installs support for NI-VXI in LabVIEW.



**Note** There are two versions of the driver. Version 2.0.x supports Linux kernel 2.4.x, and version 2.1.x supports Linux kernel 2.6.x. The `INSTALL` script autodetects which version to install.

See the `README` file on the CD-ROM for additional important information and instructions, including how to compile and load the driver.

## Technical Support

---

Technical support for Linux-specific problems is available via email and phone. Send your questions to [support@ni.com](mailto:support@ni.com) or call (512) 795-8248. See [ni.com/support/vxisupp.htm](http://ni.com/support/vxisupp.htm) for additional information and resources related to NI-VXI/NI-VISA for the PCI-MXI-2 for Linux.

For more information, visit the KnowledgeBase, a searchable online database of common questions and support issues. You can access the KnowledgeBase at [ni.com/support](http://ni.com/support) by clicking the **KnowledgeBase** link.