

COMPREHENSIVE SERVICES

We offer competitive repair and calibration services, as well as easily accessible documentation and free downloadable resources.

SELL YOUR SURPLUS

We buy new, used, decommissioned, and surplus parts from every NI series. We work out the best solution to suit your individual needs.

 Sell For Cash  Get Credit  Receive a Trade-In Deal

OBSOLETE NI HARDWARE IN STOCK & READY TO SHIP

We stock **New**, **New Surplus**, **Refurbished**, and **Reconditioned** NI Hardware.



Bridging the gap between the manufacturer and your legacy test system.

 1-800-915-6216

 www.apexwaves.com

 sales@apexwaves.com

All trademarks, brands, and brand names are the property of their respective owners.

Request a Quote

 **CLICK HERE**

PXIe-5663E

NI WCDMA/HSPA+ Toolkit Specifications

Version 1.0

This document lists specifications for the NI WCDMA/HSPA+ Toolkit.

These specifications are representative and cannot be guaranteed for different frame configurations. In addition, these specifications cannot be guaranteed on all units shipped from the factory.

Specifications are subject to change without notice. For the most recent toolkit specifications, visit ni.com/manuals.

The data sheet for the NI WCDMA/HSPA+ Toolkit contains an overview of the product, including information about the various measurements and configurations the product supports. Refer to ni.com for the data sheet.

Generation

Frequency range

NI PXIe-5673/5673E 85 MHz to 6.6 GHz

Absolute amplitude accuracy Refer to the *NI PXIe-5673*

Specifications or *NI PXIe-5673E*
Specifications.

Amplitude resolution..... Refer to the *NI PXIe-5673*

Specifications or *NI PXIe-5673E*
Specifications.

Downlink

The generation specifications for downlink were derived using the following configuration:

- Carrier frequency: 1 GHz, 1.5 GHz, 2.5 GHz
- Power level: -10 dBm to -50 dBm
- Duplex mode: DL Only (FDD)
- Signal configuration: TM6 (8 HSPDSCH/30 DPCH)
- Auto headroom enabled: True
- DL scrambling code type: Standard
- DL primary scrambling code: 0
- DL scrambling code offset: 0
- Payload data type: PN Sequence
- Payload PN order: 15

Residual RMS EVM

Residual RMS EVM with the NI PXIe-5673/5673E

Typical < 0.5%

Maximum < 1%

ACLR Dynamic Range

Adjacent channel leakage power ratio (ACLR) is the ratio of the RRC filtered mean power centered on the adjacent channel frequency to the assigned channel frequency.

ACLR signal configuration TM1 (64 DPCH)

ACLR Dynamic Range with the NI PXIe-5673

Offset Frequency (MHz)	Signal Average Power (dBm)	ACLR Dynamic Range (dB) (typical)
±5	-12	< -69
±10	-6	< -66

Uplink

The generation specifications for uplink were derived using the following configuration:

- Carrier frequency: 1 GHz, 1.5 GHz, 2.5 GHz
- Power level: -10 dBm to -50 dBm
- Duplex mode: UL Only (FDD)
- Signal configuration: 1 DPCCH + 1 DPDCH
- Auto headroom enabled: True
- UL number of channels: 2
- UL frame type: Non-PRACH
- UL scrambling code type: Long
- DPCCH slot format: 0 (SF=256)
- DPDCH slot format: 0 (SF=256)
- DPCCH relative power: -3 dB
- DPDCH relative power: -3 dB
- DPDCH branch: I
- DPDCH spreading code: 2
- DPDCH payload data type: PN Sequence
- DPDCH payload PN order: 15

Residual RMS EVM

Residual RMS EVM with the NI PXIe-5673/5673E

Typical < 0.4%

Maximum < 0.5%

ACLR Dynamic Range

Adjacent channel leakage power ratio (ACLR) is the ratio of the RRC filtered mean power centered on the adjacent channel frequency to the assigned channel frequency.

ACLR Dynamic Range with the NI PXIe-5673E

Offset Frequency (MHz)	Signal Average Power (dBm)	ACLR Dynamic Range (dB) (typical)
±5	-11	< -72
±10	-13	< -68

Analysis

Frequency range	
NI PXIe-5663/5663E.....	10 MHz to 6.6 GHz
ISM band	Supported by NI PXIe-5663/5663E
Maximum IF bandwidth	
NI PXIe-5663/5663E.....	50 MHz
Frequency measurement accuracy	Refer to the <i>NI PXIe-5663 Specifications</i> or <i>NI PXIe-5663E Specifications</i> .
Power measurement accuracy.....	Refer to the <i>NI PXIe-5663 Specifications</i> or <i>NI PXIe-5663E Specifications</i> .

Downlink

The analysis specifications for downlink were derived using the following configuration:

- Carrier frequency: 1 GHz, 1.5 GHz, 2.5 GHz
- Power level: -10 dBm to -30 dBm
- Duplex mode: DL Only (FDD)
- Signal configuration: TM6 (8 HSPDSCH/30 DPCH)
- Auto headroom enabled: True
- DL scrambling code type: Standard
- DL primary scrambling code: 0
- DL scrambling code offset: 0
- Payload data type: PN Sequence
- Payload PN order: 15

Residual RMS EVM

Residual RMS EVM with the NI PXIe-5663/5663E

Typical < 0.5%

Maximum..... < 1%

ACLR Dynamic Range

Adjacent channel leakage power ratio (ACLR) is the ratio of the RRC filtered mean power centered on the adjacent channel frequency to the assigned channel frequency.

ACLR signal configuration TM1 (64 DPCH)

ACLR Dynamic Range with the NI PXIe-5663E

Offset Frequency (MHz)	Signal Average Power (dBm)	RFSA Reference Level (dBm)	Noise Compensation	ACLR Dynamic Range (dB) (typical)
±5	-6	-4	off	< -60
±10	0	0	off	< -64

Uplink

The analysis specifications for uplink were derived using the following configuration:

- Carrier frequency: 1 GHz, 1.5 GHz, 2.5 GHz
- Power level: -10 dBm to -30 dBm
- Duplex mode: UL Only (FDD)
- Signal configuration: 1 DPCCH + 1 DPDCH
- Auto headroom enabled: True
- UL number of channels: 2
- UL frame type: Non-PRACH
- UL scrambling code type: Long
- DPCCH slot format: 0 (SF=256)
- DPDCH slot format: 0 (SF=256)
- DPCCH relative power: -3 dB
- DPDCH relative power: -3 dB
- DPDCH branch: I
- DPDCH spreading code: 2
- DPDCH payload data type: PN Sequence
- DPDCH payload PN order: 15

Residual RMS EVM

Residual RMS EVM with the NI PXIe-5663/5663E

Typical < 0.4%

Maximum < 0.5%

ACLR Dynamic Range

Adjacent channel leakage power ratio (ACLR) is the ratio of the RRC filtered mean power centered on the adjacent channel frequency to the assigned channel frequency.

ACLR Dynamic Range with the NI PXIe-5663E

Offset Frequency (MHz)	Signal Average Power (dBm)	RFSA Reference Level (dBm)	Noise Compensation	ACLR Dynamic Range (dB) (typical)
±5	-9	-15	off	< -63
±10	1	-4	off	< -67

LabVIEW, National Instruments, NI, ni.com, the National Instruments corporate logo, and the Eagle logo are trademarks of National Instruments Corporation. Refer to the *Trademark Information* at ni.com/trademarks for other National Instruments trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering National Instruments products/technology, refer to the appropriate location: **Help>Patents** in your software, the `patents.txt` file on your media, or the *National Instruments Patent Notice* at ni.com/patents.